



# Zero --- Crossing Digital





<b>Model</b>	<b>SVB - 3000VA</b>	<b>SVB - 5000VA</b>
<b>Power</b>	<b>3000VA</b>	<b>5000VA</b>
<b>Technology</b>	<b>LED Display + Relay Control + Toroidal Transformer</b>	
<b>Delay Time</b>	<b>Short dealy 3 -5sec long delay 3-7 sec</b>	
<b>Input Voltage</b>	<b>130-270Vac/100-270Vac/90-280Vac(customized) 50/60 Hz</b>	
<b>Output Voltage</b>	<b>220Vac/110Vac + 10%</b>	
<b>Connctor</b>	<b>Socket</b>	<b>Terminal block</b>
<b>Protection</b>	<b>Over Voltage(246V +4V) overload.high temperatureshort Circuit</b>	
<b>Operating Temperature</b>	<b>-20-50'C</b>	
<b>Operatiog relative humidity</b>	<b>10%RH - 102%RHNON Condensing</b>	
<b>Packing Size (CM)</b>	<b>42.5x26.5x29</b>	<b>42.5x26.5x29</b>
<b>PCS/Carton</b>	<b>1</b>	<b>1</b>
<b>G.W (KGS)</b>	<b>10</b>	<b>13</b>
<b>Package</b>	<b>Plastic bag + Color Box + Master Carton</b>	



**Zero Crossing Digital**

